

特定小電力トランシーバー メーカー別 チャンネル設定表

メーカー/ブランド		STANDARD STANDARD HORIZON		MOTOROLA			ICOM	ALINCO	KENWOOD	
Ch	周波数 (MHz)	FTH PK SR	HX	MS50	MS80	CL	IC	DJ	UBZ	
単信 11ch	422.05	01	01	1	1	1	1	b01	1	
	422.0625	02	02	2	2	2	2	b02	2	
	422.075	03	03	3	3	3	3	b03	3	
	422.0875	04	04	4	4	4	4	b04	4	
	422.1	05	05	5	5	5	5	b05	5	
	422.1125	06	06	6	6	6	6	b06	6	
	422.125	07	07	7	7	7	7	b07	7	
	422.1375	08	08	8	8	8	8	b08	8	
	422.15	09	09	9	9	9	9	b09	9	
	422.1625	10	10	10	10	10	10	b10	10	
	422.175	11	11	11	11	11	11	b11	11	
単信 9ch	422.2	1	1	12	12	12	12	L01	h1	
	422.2125	2	2	13	13	13	13	L02	h2	
	422.225	3	3	14	14	14	14	L03	h3	
	422.2375	4	4	15	15	15	15	L04	h4	
	422.25	5	5	16	16	16	16	L05	h5	
	422.2625	6	6	17	17	17	17	L06	h6	
	422.275	7	7	18	18	18	18	L07	h7	
	422.2875	8	8	19	19	19	19	L08	h8	
	422.3	9	9	20	20	20	20	L09	h9	
中継 18ch	440.025	421.575	12	01	-	21	21	1	-	1
	440.0375	421.5875	13	02	-	22	22	2	-	2
	440.05	421.6	14	03	-	23	23	3	-	3
	440.0625	421.6125	15	04	-	24	24	4	-	4
	440.075	421.625	16	05	-	25	25	5	-	5
	440.0875	421.6375	17	06	-	26	26	6	-	6
	440.1	421.65	18	07	-	27	27	7	-	7
	440.1125	421.6625	19	08	-	28	28	8	-	8
	440.125	421.675	20	09	-	29	29	9	-	9
	440.1375	421.6875	21	10	-	30	30	10	-	10
	440.15	421.7	22	11	-	31	31	11	-	11
	440.1625	421.7125	23	12	-	32	32	12	-	12
	440.175	421.725	24	13	-	33	33	13	-	13
	440.1875	421.7375	25	14	-	34	34	14	-	14
	440.2	421.75	26	15	-	35	35	15	-	15
	440.2125	421.7625	27	16	-	36	36	16	-	16
	440.225	421.775	28	17	-	37	37	17	-	17
	440.2375	421.7875	29	18	-	38	38	18	-	18
中継 9ch	440.2625	421.8125	10	1	-	39	39	19	-	h1
	440.275	421.825	11	2	-	40	40	20	-	h2
	440.2875	421.8375	12	3	-	41	41	21	-	h3
	440.3	421.85	13	4	-	42	42	22	-	h4
	440.3125	421.8625	14	5	-	43	43	23	-	h5
	440.325	421.875	15	6	-	44	44	24	-	h6
	440.325	421.8875	16	7	-	45	45	25	-	h7
	440.325	421.9	17	8	-	46	46	26	-	h8
	440.3625	421.9125	18	9	-	47	47	27	-	h9