

特定小電力トランシーバー メーカー別 チャンネル設定表

メーカー / ブランド			STANDARD STANDARD HORIZON		MOTOROLA			ICOM	ALINCO	KENWOOD
Ch	周波数 (MH z)		FTH PK SR	HX	MS50	MS80	CL	IC	DJ	UBZ
単信 11ch	422.0500		01	01	1	1	1	1	b01	1
	422.0625		02	02	2	2	2	2	b02	2
	422.0750		03	03	3	3	3	3	b03	3
	422.0875		04	04	4	4	4	4	b04	4
	422.1000		05	05	5	5	5	5	b05	5
	422.1125		06	06	6	6	6	6	b06	6
	422.1250		07	07	7	7	7	7	b07	7
	422.1375		08	08	8	8	8	8	b08	8
	422.1500		09	09	9	9	9	9	b09	9
	422.1625		10	10	10	10	10	10	b10	10
	422.1750		11	11	11	11	11	11	b11	11
単信 9ch	422.2000		1	1	12	12	12	12	L01	h1
	422.2125		2	2	13	13	13	13	L02	h2
	422.2250		3	3	14	14	14	14	L03	h3
	422.2375		4	4	15	15	15	15	L04	h4
	422.2500		5	5	16	16	16	16	L05	h5
	422.2625		6	6	17	17	17	17	L06	h6
	422.2750		7	7	18	18	18	18	L07	h7
	422.2875		8	8	19	19	19	19	L08	h8
	422.3000		9	9	20	20	20	20	L09	h9
中継 18ch	440.0250	421.575	12	01	-	21	21	1	b12	1
	440.0375	421.5875	13	02	-	22	22	2	b13	2
	440.0500	421.6000	14	03	-	23	23	3	b14	3
	440.0625	421.6125	15	04	-	24	24	4	b15	4
	440.0750	421.6250	16	05	-	25	25	5	b16	5
	440.0875	421.6375	17	06	-	26	26	6	b17	6
	440.1000	421.6500	18	07	-	27	27	7	b18	7
	440.1125	421.6625	19	08	-	28	28	8	b19	8
	440.1250	421.6750	20	09	-	29	29	9	b20	9
	440.1375	421.6875	21	10	-	30	30	10	b21	10
	440.1500	421.7000	22	11	-	31	31	11	b22	11
	440.1625	421.7125	23	12	-	32	32	12	b23	12
	440.1750	421.7250	24	13	-	33	33	13	b24	13
	440.1875	421.7375	25	14	-	34	34	14	b25	14
	440.2000	421.7500	26	15	-	35	35	15	b26	15
	440.2125	421.7625	27	16	-	36	36	16	b27	16
	440.2250	421.7750	28	17	-	37	37	17	b28	17
	440.2375	421.7875	29	18	-	38	38	18	b29	18
中継 9ch	440.2625	421.8125	10	1	-	39	39	19	L10	h1
	440.2750	421.8250	11	2	-	40	40	20	L11	h2
	440.2875	421.8375	12	3	-	41	41	21	L12	h3
	440.3000	421.8500	13	4	-	42	42	22	L13	h4
	440.3125	421.8625	14	5	-	43	43	23	L14	h5
	440.3250	421.8750	15	6	-	44	44	24	L15	h6
	440.3375	421.8875	16	7	-	45	45	25	L16	h7
	440.3500	421.9000	17	8	-	46	46	26	L17	h8
	440.3625	421.9125	18	9	-	47	47	27	L18	h9